

TA9210D

12.5 W CW 0.03 – 4.0 GHz GaN Power Transistor

Application Note: TA9210D EVB F

Application Note

200 MHz~2700 MHz

20 V, 50 mA

Rev-2.3

List of Contents

- 1 General Description
- 2 TA9210D-EVB-F Board Details
- 3 TA9210D-EVB-F Bill of Material
- 4 TA9210D-EVB-F Biasing sequence
- 5 TA9210D-EVB-F Board Measurement Summary
- 6 TA9210D-EVB-F Board Measurement Results

1. General Description

The TA9210D is a broadband capable 12.5 W GaN power transistor covering 30 MHz to 2.7 GHz frequency band with a single match. TA9210D is usable up to 4 GHz. The input and output can be matched for best power and efficiency for the desired band.

The TA9210D is packaged in a compact, low-cost Quad Flat No lead (QFN) 3 x 6 x 0.75 mm, 32 leads plastic package. TA9210D-EVB-F is tuned from 200 MHz to 2700 MHz.

2. TA9210D-EVB-F Board Details




Figure 2.1 TA9210D-EVB-F 200 MHz ~ 2700 MHz Schematic and EVB Layout

3. TA9210D-EVB-F Bill of Material

Component ID	Value	Manufacturer	Recommended Part Number
C11	39 pF	AVX	600S390FT250XT
C12	47 pF	AVX	600S470FT250XT
R31	2.7 Ω	Vishay	CRCW06032R70FKEAHP
C32	1.6 pF	AVX	600S1R6BW250XT
C33	1.2 pF	AVX	600S1R2BW250XT
L34, L41	1 nH	Coil craft	0402HP-1N0XJRW
C35	1 pF	AVX	600S1R0BW250XT
C42	1.5 pF	AVX	600S1R5BW250XT
L51	82 nH	Coil craft	1008HQ-82NXGLC
C52	0.1 μ F, 50 V	Murata	GRM31C5C1H104JA01L
C53	10 μ F, 50 V	Murata	GRM32ER71H106KA12L
C54	100 μ F, 63 V	Nichicon	UPW1J101MPD1TD
D71	7.5 V Zener	On Semiconductor	SZMMSZ5236BT1G
C72	0.1 μ F, 10 V	AVX	0603ZC104K4T2A
R75	20 Ω	Vishay	CRCW060320R0FKEAHP
C78	47 μ F, 16 V	Murata	GRM32ER61C476ME15L
Q1	12.5W power transistor	Tagore Tech	TA9210D
PCB	Rogers RO4350B, 20 mils, 2 oz copper		

Table 3.1 TA9210D-EVB-F BOM

4. TA9210D-EVB-F Biasing Sequence

Turn ON Device	Turn OFF Device
1. Set V_G to -5 V 2. Set V_D to +20 V 3. Adjust V_G to reach required I_{DQ} current 4. Apply RF power	1. Turn RF power off 2. Turn off V_D 3. Turn off V_G

Table 4.1 TA9210D-EVB-F Bias and Sequencing

5. TA9210D-EVB-F Board Measurement Summary

Frequency (MHz)	S21 Gain(dB)	S11 (dB)	S22 (dB)	Psat (dBm)	PAE (%) @ Psat
200	18.9	-6.9	-7.4	37.2	75
500	18.1	-6.8	-4.6	37.8	66
1000	16.6	-5.9	-3.7	38.5	58
1500	15.8	-6.7	-3.7	38.2	45
2000	14.4	-5.9	-6.3	39.5	40
2700	13.5	-9.9	-15.6	38.2	50

Table 5.1 TA9210D-EVB-F 20 V, 50 mA Electrical Characteristics Summary

6. TA9210D-EVB-F Test Results

All the tests are carried out at room temperature.

6.1. S parameters




Figure 6.1.1. S parameters of TA9210D-EVB-F 20 V, 50 mA

6.2. Large Signal Test Results

Gain and PAE Vs P_{OUT} data [V_d=20 V, I_{DQ}=50 mA, CW]




Figure 6.2.1. Gain and PAE vs P_{OUT} of TA9210D-EVB-F for 20 V, 50 mA 0.2-1 GHz




Figure 6.2.2. Gain and PAE vs P_{OUT} of TA9210D-EVB-F for 20 V, 50 mA 1.2-1.6 GHz




Figure 6.2.3. Gain and PAE vs P_{OUT} of TA9210D-EVB-F for 20 V, 50 mA 1.8-2.7 GHz

6.3. ACPR and AACPR Test Results

Bias :20 V, 50 mA




Figure 6.3.1. ACPR vs P_{OUT} of TA9210D-EVB-F for 20 V, 50 mA 0.2-1 GHz




Figure 6.3.2. ACPR vs P_{OUT} of TA9210D-EVB-F for 20 V, 50 mA 1.5-2.7 GHz




Figure 6.3.3. AACPR vs P_{OUT} of TA9210D-EVB-F for 20 V, 50 mA 0.2-1 GHz




Figure 6.3.4. AACPR vs P_{OUT} of TA9210D-EVB-F for 20 V, 50 mA 1.5-2.7 GHz

Bias :20 V, 600 mA




Figure 6.3.5. ACPR vs P_{OUT} of TA9210D-EVB-F for 20 V, 50 mA 0.2-1 GHz




Figure 6.3.6. ACPR vs P_{OUT} of TA9210D-EVB-F for 20 V, 50 mA 1.5-2.7 GHz




Figure 6.3.7. AACPR vs P_{OUT} of TA9210D-EVB-F for 20 V, 50 mA 0.2-1 GHz




Figure 6.3.8. AACPR vs P_{OUT} of TA9210D-EVB-F for 20 V, 50 mA 1.5-2.7 GHz

Edition Revision 2.3 - 2024-07-30

Published by

Tagore Tech Inc.

601 W Campus Dr. Ste C1

Arlington Heights, IL 60004, USA

©2024 All Rights Reserved

Legal Disclaimer

The information provided in this document shall in no event be regarded as a guarantee of conditions or characteristics. Tagore Tech assumes no responsibility for the consequences of the use of this information, nor for any infringement of patents or of other rights of third parties which may result from the use of this information. No license is granted by implication or otherwise under any patent or patent rights of Tagore Tech. The specifications mentioned in this document are subject to change without notice.

Information

For further information on technology, delivery terms and conditions and prices, please contact Tagore Tech: support@tagoretech.com.